

Spec Sheet: S120UV Silicon Power Meter Optical Head

Description:

The S120UV is an optical power meter head designed to be used directly with the ThorLabs PM100, PM30 and PM300 console system to measure light from the ultraviolet over the visible and near infrared wavelength range of 200 to 1100nm and provide a NIST traceable optical power measurement. The optical power meter head will detect light over the power range of 50nW to 50mW. An EEPROM located in the DB9 mating connector will store the NIST calibrated spectral response curve required to provide an accurate power reading.

The S120UV housing includes a threaded input that is compatible with any number of ThorLabs 1" and 0.5" threaded accessories. This allows convenient mounting of external optics, fiber adapters, light filters, and apertures. A 8-32 threaded mounting hole is provided to accommodate posts and post holders (an M4 adapter is included).

The removable annular IR viewing target allows conveniently centering the measured beam to the active area of the photo-diode. The target works from 400 to 640nm and 800 to 1700nm.

Specifications:

Spectra Range:	200 – 1100nm	Optical Power Range:	50nW – 50mW (@980nm)
Sensor:	Silicon	Resolution:	0.1nW
Sensor Size:	10mm x 10mm sq. (0.39" x 0.39")	Measurement Standard:	NIST Traceable
Input Aperture:	9.5mm Diameter (0.37")	Measurement Uncertainty:	+/- 5%
Distance to ND Filter:	3.3mm (0.13")	Operating Temperature:	5°C to 40°C
Distance to Detector:	5.8mm (0.23")	Storage Temperature:	-20°C to 70°C
		Damage Threshold:	50W/cm ²

Cleaning and Maintenance:

There are no serviceable parts in the S120UV optical head. The housing may be cleaned by wiping with a soft damp cloth. When cleaning the aperture filter of the S120UV, treat it as any other fine optic. Gently blow off any debris using compressed air and wipe gently with an optic tissue wetted with propanol. If you suspect a problem with your S120UV please call ThorLabs and an engineer will be happy to assist you.

As long as the sensor has not been exposed to excessive optical power, the calibration should be very stable over long periods of time (well over a year). However, the detector should be calibrated once a year to ensure accuracy.

Console - Sensor Compatibility:

PM100:	Compatible from firmware version 1.62 (September 2005) Please contact ThorLabs for a free upgrade of the console firmware.
PM30:	Compatible
PM300, PM300E:	Compatible
S100:	Not compatible, no upgrade possible

WEEE

As required by the WEEE (Waste Electrical and Electronic Equipment Directive) of the European Community and the corresponding national laws, Thorlabs offers all end users in the EC the possibility to return “end of life” units without incurring disposal charges.

This offer is valid for Thorlabs electrical and electronic equipment

- sold after August 13th 2005
- marked correspondingly with the crossed out “wheelie bin” logo (see fig. 1)
- sold to a company or institute within the EC
- currently owned by a company or institute within the EC
- still complete, not disassembled and not contaminated

As the WEEE directive applies to self contained operational electrical and electronic products, this “end of life” take back service does not refer to other Thorlabs products, such as

- pure OEM products, that means assemblies to be built into a unit by the user (e. g. OEM laser driver cards)
- components
- mechanics and optics
- left over parts of units disassembled by the user (PCB's, housings etc.).

If you wish to return a Thorlabs unit for waste recovery, please contact Thorlabs or your nearest dealer for further information.

Waste treatment on your own responsibility

If you do not return an “end of life” unit to Thorlabs, you must hand it to a company specialized in waste recovery. Do not dispose of the unit in a litter bin or at a public waste disposal site.

Ecological background

It is well known that WEEE pollutes the environment by releasing toxic products during decomposition. The aim of the European RoHS directive is to reduce the content of toxic substances in electronic products in the future.

The intent of the WEEE directive is to enforce the recycling of WEEE. A controlled recycling of end of live products will thereby avoid negative impacts on the environment.



Crossed out “wheelie bin” symbol